



EVG T5 Glas Kompatibilitätsliste

	Length	Serial	Brand	Ballast Model	Lamp Mode	Compatibility (Y or N)	Emergency (Y or N)	Remark	
7989005 Tube Elektra T5 EVG 2400LM-16W	1149	66	Osram	QTP5 1x14-35	1	Y	N		
	1149	67	Osram	QTP5 2x14-35	2	Y	N		
	1149	68	Osram	QT-FIT5 1x14-35	1	Y	N		
	1149	69	Osram	QT-FIT5 2x14-35	2	Y	N		
	1149	70	Philips	HF-S 128-35 TL5 II	1	Y	N	updated on 19.06.28	
	1149	71	Philips	HF-S 221-28 TL5 II	2	Y	N	updated on 19.06.28	
	1149	72	Osram	QTI 1x28/54/35/49 GII	1	Y	Y		
	1149	73	Osram	QTI 2x28/54/35/49 GII	2	Y	Y	Slight flicker when light up	
	1149	74	Philips	HF-P 1 14-35 TL5 HE III IDC	1	Y	Y		
	1149	75	Philips	HF-P 2 14-35 TL5 HE III IDC	2	Y	N		
	1149	76	Philips	HF-P 2 14-35 TL5 HE EII 220-240	2	Y	N	updated on 19.06.28	
	1149	77	Philips	HF-Pi 2 28/35/49/54 TL5 EII 220-240	2	Y	Y		
	1149	78	Tridonic	PC 1x14-35 T5 PRO lp	1	Y	N		
	1149	79	Tridonic	PC 2x14-35 T5 PRO lp	2	Y	N		
	1149	80	Tridonic	PC 1x14-35 T5 TOP lp	1	Y	N		
	1149	81	Tridonic	PC 2/14-35/49/54 T5 PRO-M lp	2	Y	N		
	1149	82	BAG	BCS 35.1FX-11/220-240	1	Y	N		
	1149	83	BAG	BCS 35.2FX-11/220-240	2	Y	N		
	1149	84	MECTRONIC	ERC	1	Y	N	updated on 19.06.28	
	1149	85	Tridonic	PC 2x14-28 T5 TOP lp	2	Y	N		
	1149	86	Helvar	EL1x14-35ngn5	1	Y	N		
	1149	87	Osram	QIZ 5 1x28/220-240	1	N	N	High power	
	1149	88	Osram	QIZ 5 2x28/220-240	2	N	N	High power	
	1149	89	Philips	HF-R 114-35 TL5 EII	1	N	N	No light	
	1149	90	Philips	HF-P 2 14-35 TL5 HE 220-240	2	N	N	No light	
	1149	91	Philips	HF-Pi 1 28/35/49/54 TL5 EII 220-240	1	N	N	High power	
	1149	92	Philips	HF-Pi 1 28/35/49/80 TL5 EII 220-240	1	N	N	High power	
	1149	93	Philips	HF-Pi 2 28/35/49/80 TL5 EII 220-240	2	N	N	High power	
	1149	94	Tridonic	PC 1x28 T5 TEC lp	1	N	N	High power	
	1149	95	Tridonic	PC 2x28 T5 TEC lp	2	N	N	High power	
	1149	96	Philips	PCA 1x28/54 T5 EXCEL one 4all lp	1	N	N	High power	
	1149	97	Philips	PCA 1x28/54 T5 ECO lp	1	N	N	High power	
	1149	98	Philips	EB-C 128 TL5	1	N	N	Power is too high and unstable	
	1149	99	Philips	EB-C 228 TL5	2	N	N	Power is too high and unstable	
	1149	100	Philips	HF-Pi 2 28/35/49/80 TL5 EII	2	N	N	Low power	
	1149	101	Osram	EZP5 1x28/220-240	1	N	N	Low power	
	1149	102	Tridonic	PC 1/14-35/49/54 T5 PRO-M lp	1	Y	N		
	1149	103	Tridonic	PC 1/14-35/49/80 T5 PRO-M lp	1	Y	N		
	1149	104	Helvar	EL 2x14-35ngn5	2	Y	N		
	1149	105	eIT	BE-214-35-T5-S	2	Y	N		
	1149	106	Tridonic	PC 2x14-35 T5 TOP lp	2	Y	N		
	1149	107	Tridonic	PC 2x14-35 T5 TOP lp	2	Y	N		
	1149	108	Osram	QTI DALI 1x28/54 DIM	1	N	N	High power	
	1149	109	Osram	QTI DALI 2x28/54 DIM	2	N	N	High power	
	1149	110	VOSSLÖH	ELxc 235.857	2	Y	Y	High power	
	7989001 Tube Elektra T5 EVG 4000LM-27W	1149	111	Osram	QTP-OPTIMAL 1X54-58	1	Y	Y	
		1149	112	Osram	QTP-OPTIMAL 2X54-58	2	Y	N	updated on 19.06.28
		1149	113	Osram	QT-FIT 5/8 1X54-58	1	Y	N	
		1149	114	Osram	QT-FIT 5/8 2X54-58	2	Y	N	updated on 19.06.28
		1149	115	Osram	QTI 1X28/54/35/49 GII	1	Y	N	
		1149	116	Osram	QTI 2X28/54/35/49 GII	2	Y	N	
		1149	117	Philips	HF-S 154 TL5 II	1	Y	N	updated on 19.06.28
		1149	118	Philips	HF-S 254 TL5 II	2	Y	N	updated on 19.06.28
		1149	119	Philips	HF-P 154/55 T5 HO/PL-L III IDC	1	Y	Y	
		1149	120	Philips	HF-P 254/55 T5 HO/PL-L III IDC	2	Y	Y	
		1149	121	Helvar	EL 254A 26M	2	Y	N	updated on 19.06.28
		1149	122	Tridonic	PC 1X54 T5 TOP lp	1	Y	Y	
		1149	123	Tridonic	PC 2X54 T5 TOP lp	2	Y	N	updated on 19.06.28
		1149	124	Tridonic	PC 1X54 T5 PRO lp	1	Y	Y	
		1149	125	Tridonic	PC 2X54 T5 PRO lp	2	Y	N	
		1149	126	BAG	BCS 54.1FR-01/220-240	1	Y	N	
		1149	127	BAG	MLS 80.1FR-11/220-240	1	Y	N	updated on 19.06.28
		1149	128	VOSSLÖH	ELxc 154.864	1	Y	N	updated on 19.06.28
		1149	129	Osram	QTP5 2X54	2	Y	N	updated on 19.06.28
		1149	130	Philips	HF-R 154 TL5 EII	1	Y	N	updated on 19.06.28
		1149	131	Philips	HF-Pi 1 28/35/49/54 TL5 EII 220-240	1	N	N	230V Flicker
		1149	132	Philips	HF-Pi 2 28/35/49/54 TL5 EII 220-240	2	N	N	Flicker after light up
		1149	133	Tridonic	PCA 1X28/54 T5 ECO lp	1	N	N	Power is too low
	1149	134	Tridonic	PC 2 14-35/49/54 T5 PRO-M lp	2	N	N	Went out after light up	
	1149	135	Helvar	EL 1X54ngn5	1	N	N	High power	
	1149	136	Helvar	EL 2X54ngn5	2	N	N	High power	
	1149	137	Helvar	EL 1X54sc	1	N	N	High power	
	1149	138	Helvar	EL 2X54sc	2	N	N	High power	
	1149	139	Helvar	EL 1X54Dim	1	N	N	High power	
	1149	140	Helvar	EL 2X54Dim	2	N	N	High power	
	1149	141	BAG	MLS80.1/54.2FR-11/220-240	1	Y	N	updated on 19.06.28	
	1149	142	Osram	QTI DALI 1x28/54 DIM	1	N	N	High power	
	1149	143	Osram	QTI DALI 2x28/54 DIM	2	N	N	Low Power	



7989006 Tube Elektra T5 EVG 4200LM-26W	1449	188	Osram	QT-FIT5 1X49	1	Y	N	
	1449	189	Osram	QT-FIT5 2X49	2	Y	N	
	1449	190	Osram	QTP5 1X49	1	Y	Y	
	1449	191	Osram	QTP5 2X49	2	Y	Y	
	1449	192	Philips	HF-Pi 1 28/35/49/54 TL5 EII 220-240	1	Y	Y	
	1449	193	Philips	HF-Pi 2 28/35/49/54 TL5 EII 220-240	2	Y	Y	
	1449	194	Philips	HF-S 149 TL5 II	1	Y	Y	
	1449	195	Philips	HF-S 249 TL5 II	2	Y	Y	
	1449	196	Philips	HF-P 149 TL5 HO III IDC	1	Y	Y	
	1449	197	Philips	HF-P 249 TL5 HO III IDC	2	Y	Y	
	1449	198	Philips	HF-P 149 TL5 HO EII 220-240	1	Y	N	
	1449	199	Philips	HF-Pi 1 28/35/49/80 TL5 EII 220-240	1	Y	Y	
	1449	200	Philips	HF-P Xi 249 TL5 EII 220-240	2	Y	Y	
	1449	201	Tridonic	PC 1X49 T5 TOP Ip	1	Y	N	
	1449	202	Tridonic	PC 2X49 T5 TOP Ip	2	Y	N	
	1449	203	Tridonic	PC 1X49 T5 PRO Ip	1	Y	N	
	1449	204	Tridonic	PC 2X49 T5 PRO Ip	2	Y	N	
	1449	205	BAG	BCS 49.1FX-11/220-240	1	Y	N	
	1449	206	VOSSLOH	ELXc 249.859	2	Y	N	
	1449	207	Osram	QTI 1X35/49/80 DIM	1	N	N	Went out after light up
	1449	208	Osram	QTI 2X35/49/80 DIM	2	N	N	Low power
	1449	209	Osram	QTI 1X35/49/80 GII	1	Y	N	Low power
	1449	210	Osram	QTI 2X35/49/80 GII	2	N	N	Low power
	1449	211	Osram	QTI 1X28/54/35/49 GII	1	N	Y	Low power
	1449	212	Osram	QTI 2X28/54/35/49 GII	2	N	N	Low power
	1449	213	Osram	QTI 1x35/49/80 GII	1	Y	N	
	1449	214	Osram	QTI 2X35/49/80	2	N	N	Low power
	1449	215	Osram	QT-FQ 2X49/230-240 CW	2	N	N	Low power
	1449	216	Philips	HF-Pi 2 28/35/49/80 TL5 EII 220-240	2	N	Y	Low power
	1449	217	Philips	HF-Pi 2 28/35/49/80 TL5 EII	2	N	N	Low power
1449	218	Tridonic	PC 2 14-35/49/54 T5 PRO-M Ip	2	N	N	Low power	
1449	219	Tridonic	PCA 2X35/49 T5 ECO Ip	2	N	N	Flicker,uncontinuously no light after several start-ups.	
1449	220	BAG	MLS 80.1/54.2FR-11/220-240	1	N	N	High power	
1449	221	Helvar	EL 1x49ngn5	1	N	N	High power	
1449	222	Osram	QTI DALI 2x35/49 DIM	2	N	N	Flicker	
1449	223	Tridonic	PC 1/14-35/49/54 T5 PRO-M Ip	1	N	N	Low power	
1449	224	Tridonic	PC 1/14-35/49/80 T5 PRO-M Ip	1	N	N	Low power	
1449	225	BAG	BCS49.2FX-11/220-240	2	N	N	Low power	
1449	226	BAG	MLS80.1FR-11/220-240	1	N	N	High power	
1449	227	Helvar	EL2x49s	2	N	N	Flicker	
1449	228	Helvar	EL2x49ngn5	2	N	N	Flicker	
7989002 Tube Elektra T5 EVG 5600LM -37W	1449	229	Osram	QTI 2X35/49/80 GII	2	Y	Y	
	1449	230	Osram	QTP5 1X80	1	Y	Y	
	1449	231	Osram	QT-FQ 2X80	2	Y	N	Slight Flicker after light up
	1449	232	Osram	QTI 2X35/49/80 DIM	2	Y	N	updated on 19.06.28
	1449	233	Philips	HF-Pi 1 80 TL5/PL-L III IDC	1	Y	N	
	1449	234	Philips	HF-P 2 80 TL5/PL-L III IDC	2	Y	N	
	1449	235	Tridonic	PC 2/80 T5 INDUSTRY	2	Y	N	updated on 19.06.28
	1449	236	Tridonic	PC 1X80 T5 PRO Ip	1	Y	Y	
	1449	237	Tridonic	PC 2X80 T5 PRO Ip	2	Y	Y	
	1449	238	Tridonic	PCA 2X80 T5 ECO Ip	2	Y	N	updated on 19.06.28
	1449	239	Tridonic	PCA 2X80 T5 EXCEL one4all Ip	2	Y	N	updated on 19.06.28
	1449	240	BAG	MLS 80.1/54.2 FR-11/220-240	1	Y	N	
	1449	241	BAG	MLS 80.1 FR-11/220-240	1	Y	N	
	1449	242	BAG	BCS 80.1 FX-11/220-240	1	Y	N	updated on 19.06.28
	1449	243	BAG	BCS 80.2 FX-11/220-240	2	Y	N	
	1449	244	Helvar	EL 2X80ngn5	2	Y	N	updated on 19.06.28
	1449	245	Osram	QTI 1X35/49/80 GII	1	N	Y	No Light
	1449	246	Osram	QTI 2X35/49/80	2	N	N	uncontinuously no light after several start-ups.
	1449	247	Osram	QTI 1X35/49/80 DIM	1	N	N	Flicker until no light after start-ups
	1449	248	Philips	HF-Pi 1 28/35/49/80 TL5 EII 220-240	1	N	N	Low power
	1449	249	Philips	HF-Pi 2 28/35/49/80 TL5 EII 220-240	2	N	N	Low power
	1449	250	Philips	HF-Pi 2 28/35/49/80 TL5 EII	2	N	N	Low power
	1449	251	Tridonic	PC 1/80 T5 INDUSTRY	1	N	N	
	1449	252	Tridonic	PCA 1X80 T5 BASIC Ip	1	N	N	No light after several start ups
	1449	253	Helvar	EL 1X80ngn5	1	N	N	High Power
	1449	254	Helvar	EL 1X80Dim	1	N	N	High Power
	1449	255	Osram	QTI DALI 1x35/49/80 DIM	1	N	N	No light
	1449	256	Osram	QTI DALI 2x35/49/80 DIM	2	N	N	No light
	1449	257	Philips	HF-P xt 180 TL5 EII 220-240	1	N	N	No light
	1449	258	Tridonic	PC 1/14-35/49/80 T5 PRO-M Ip	1	N	N	Low power
1449	259	Helvar	EL1x80ngn5	1	N	N	High Power	
1449	260	Helvar	EL2x80ngn5	2	N	N	High Power	
1449	261	VOSSLOH	Type ELXc 180.634	1	Y	N		
1449	262	VOSSLOH	Type ELXc 280.637	2	Y	N		